1. Install the camera search tool , download it from www.mydownload.store



2. Plug out one camera from the NVR PoE port, and connect your PC to NVR PoE port.

PoE ports all isolated with the LAN port



3. Run the search tool and operate following the steps bellow:

3.1 Upgrade new firmware

IP Address	эттэ	Wodel	Title Name	Trevies	Firmware Version	s	tatus	All subm	53.	
≥ 192, 149, 100, 212	80	19500L	k-284 SEURE			1	9:00:22 Alarm:motio	alese	EP0000000298437	
		Lonk p Cluick access Desktop Libraries This PC	Image: Section (Section (
Batch Beset	Batch B	eboot IP Batch Se	tting 6002	./60112	Batch Set Lunguage – Batch	Syno Tine Batch Set	Password			

4. Do not power off , the update will finish in 2 minutes.

5. When camera come back , select all and click Batch Reset button .

If there is some customed info such as logo, OEM message you want remove , Clean old configuration via C:\Program Files (x86)\SearchTools\SearchTools\firmware_clean_all_cust.bin

	Start Sea	rch Export to Exc	el admin	123456	QE Automatic printing		10tal:	s Selete
P Address	XTT?	Medel	Title Nume	Preview	Firmware Version	Status		All sub
192.168.16.27	80	1MSOOL	Cuners		YNSOOL_AF_V0_BU_Y_BH-RTNP-HS_L V3.0.2.1 h	Legin success		olose
Batch Reset	Batch Be	noot If Batch Se	tting 500	1/60 0 Z	Batch Set Language Batch Symo Time Batch :	Set Passwerd		